


 999.00 EUR
 incl. 19% VAT, plus [shipping](#)

Support:  [Specifications](#)

Enhance commercial fleet safety and efficiency with the AMOS-825 system. Powered by a 1.0GHz NXP i.MX 6Quad Cortex-A9 quad-core SoC, this fanless small form factor system has been specifically designed for demanding compute-intensive fleet management, navigation and infotainment applications. Featuring a 1.0GHz NXP i.MX 6Quad ARM Cortex-A9 quad-core SoC, the VIA AMOS-825 delivers a highly-capable and power-efficient system for compute- and multimedia-intensive in-vehicle infotainment and navigation applications.

With its 3G networking support (provided separately through an optional expansion card) and its rich connectivity, the AMOS-825 can serve as a powerful data collection and control center on the go within vehicles. GPS, Wi-Fi, Ethernet, USB, COM, and HDMI ports make connecting devices very easy. A completely fanless system with a ruggedized design and automotive compatible power options make it into your one-stop solution for in-vehicle applications.

| | |
|---------------------|--|
| Model Name | AMOS-825 |
| Processor | 1.0GHz NXP i.MX 6Quad Cortex-A9 quad-core SoC |
| System Memory | 1GB DDR3 SDRAM onboard |
| Storage | 16GB eMMC Flash memory |
| Boot Loader | 4MB SPI Flash ROM |
| Graphics | Vivante GC2000 GPU 3 independent, integrated 3D/2D and video graphics processing units Graphics engine supporting OpenGL® ES 2.0, OpenCL and OpenVG™ 1.1 hardware acceleration Supports MPEG-2, VC-1 and H.264 video decoding up to 1080p Supports SD encoding |
| LAN | Micrel KSZ9031RNX Gigabit Ethernet transceiver with RGMII support IEEE 802.11b/g/n Wi-Fi Bluetooth 4.0 |
| Wi-Fi/Bluetooth/GPS | MAX-7 u-blox 7 GPS/GNSS |
| Audio | NXP SGTL5000 low power stereo codec |
| USB | SMSC USB2514 USB 2.0 high-speed 4-port hub controllers |
| CAN | TI SN65HVD1050 EMC optimized CAN transceiver |

| | |
|------------------------------------|--|
| Expansion I/O | 1 miniPCIe slot 1 Micro USB 2.0 OTG port 1 9-pin D-sub connector (supports 2 CAN bus and 1 COM TX/RX for debug) 1 SCSI 50-pin D-sub connector (Backlight power, Dual-channel LVDS, 4 GPIO, I ² C, Line-out and Mic-in) |
| Front Panel I/O | 1 Mic-in 1 Reset button 2 LEDs for power & WPAN/WWAN/WLAN status 1 Antenna hole 1 4-pole Phoenix DC jack 2 USB 2.0 ports 1 Gigabit Ethernet port 2 Antenna connectors for Wi-Fi/BT and GPS |
| Back Panel I/O | 9 ~ 36V DC-in (typical: 7W) Android 6.0 Watchdog timer, CAN bus 0°C ~ 60°C 0% ~ 90% @ 45° C (non-condensing) With onboard eMMC 7Grms, IEC 60068-2-64, random, 5 ~ 500Hz, 1hr/axis |
| Power Supply | |
| Operating System | |
| VIA Smart ETK | |
| Operating Temperature | |
| Operating Humidity | |
| Vibration Loading During Operation | |
| Shock During Operation | With onboard eMMC 70G, IEC 60068-2-27, half sine, 11ms duration |
| Bottom Opening Covers | Open window with removable door plate to access Micro SD and miniPCIe slots |
| Mechanical Construction | Aluminum top chassis housing Metal chassis housing Dual removable front & rear metal face plate |
| Mounting | Wall/DIN Rail/VESA mountable |